

Copper


Copper is a 99.9% commercially pure material with excellent electrical and thermal conductivity properties.


It is mostly used for electronics, heat exchangers, heat sinks, engine parts as well as in a variety of industry applications that require good conductivity.


Printing in copper offers freedom of design and enables optimal functionality with few restrictions.



TENSILE TEST BEHAVIOR OF COPPER







*LOM Images - DM Cu etched with Klemm's reagent plus polarized light

These representative data were tested, measured, or calculated using standard methods and are subject to change without notice. Markforged makes no warranties of any kind, express or implied, including, but not limited to, the warranties of merchantability, fitness for a particular use, or warranty against patent infringement; and assumes no liability in connection with the use of this information. The data listed here should not be used to establish design, quality control, or specification limits, and are not intended to substitute for your own testing to determine suitability for your particular application. Nothing in this sheet is to be construed as a license to operate under or a recommendation to infringe upon any intellectual property right.

99.9% pure material		
Excellent thermal and elect	rical conductivity	

Composition	Weight%
Copper	99.9
Iron	0.04
Nickel	0.015
Carbon	0.02
Oxygen	0.003
Others	Balance

Density	Hardness (HRC)
Ultimate tensile strength (MPa)	195
Yield strength [MPa]	30
Elongation [%]	35
Sintered density [g/cm3]	8.6